

726-24AC/10A

726-24AC/18A

24VAC Power Supplies for Video Cameras



- **Individually Protected Outputs**
- **Self-Resetting Circuit Breakers**
- **Isolates Power Problems to Maximize Camera Up Time**



- **Power, Protection and Interconnects All in One Box**
- **Rugged Reliability Proven Worldwide**
- **Locking Steel Case**
- **110/220V, 50/60 Hz Input**

Choose the supply to match your needs:

For **Low Current Cameras**, the **726-24AC/10A** includes:

- **8 individual switched outputs** with separate barrier blocks, fused at **1.1 amps** each.
- Total power supply current is 10 amps.
- A typical configuration can power 8 video cameras which draw less than 1.1 ampere each.
- This supply is designed for use with low current cameras

For **High Current Cameras**, the **726-24AC/18A** includes:

- **4 individual switched outputs** with separate barrier blocks, fused at **4.5 amps** each.
- Total power supply current is 18 amps.
- A typical configuration can power 4 video cameras which draw up to 4.5 amperes each.
- This supply is designed for use with high current cameras.

AES Corporation

Call **1-800-237-6387**

285 Newbury Street • Peabody, MA 01960 USA

Tel +1-978-535-7310 • Fax +1-978-535-7313

<http://www.aes-security.com>

Copyright AES Corporation 2006—All Rights Reserved
726-24AC.P 04/25/06



4.726-24AC (1/2)

Model 726-24AC/10A Power Supply

- **Input:** 110/220V, 50-60 Hz, jumper selectable
- **Output Power:** 24 VAC, 10 amps total
- **Application:** 24VAC video cameras and/or monitors.
- **Output Configuration:** 8 individual, switched outputs, fused at 1.1 amps each. Maximum current is 10 amps.
- **Protection:**
 - PTC self-resetting fuses on each of the outputs. (PTC fuses are reset by removing the load)
 - Input and Output of Main supply unit are protected by circuit breakers and an internal fuse
 - Circuit breaker on front of case for AC input side of supply.
- **Size:** 14 x 14.25 x 6 inches (36 x 37 x 15 cm)
- **Weight:** 42 pounds; 19 kilograms
- **Indicator:** Light for AC input
- **Terminals:** Barrier Blocks
- **Switches:** 8 switches to turn on/off 8 individual outputs
- **Ordering:** Part Number 726-24AC/10A

Model 726-24AC/18A Power Supply

- **Input:** 110/220V, 50-60 Hz, jumper selectable
- **Output Power:** 24 VAC, 18 amps total
- **Application :** 24VAC video cameras and/or monitors.
- **Output Configuration:** 4 individual, switched outputs, fused at 4.5 amps each. Maximum current is 18 amps.
- **Protection:**
 - PTC self-resetting fuses on each of the outputs. (PTC fuses are reset by removing the load)
 - Input and Output of Main supply unit are protected by circuit breakers and an internal fuse
 - Circuit Breaker on front of case for AC input side of supply.
- **Size:** 14 x 14.25 x 6 inches (36 x 37 x 15 cm)
- **Weight:** 46 pounds; 19 kilograms
- **Indicator:** Light for AC input
- **Terminals:** Barrier Blocks
- **Switches:** 4 switches to turn on/off 4 individual outputs
- **Ordering:** Part Number 726-24AC/18A



For more information

Call 800-237-6387 / 978-535-7310

285 Newbury Street • Peabody, MA 01960 USA

Tel +1-978-535-7310 • Fax +1-978-535-7313

Copyright AES Corporation 2006—All Rights Reserved
726-24AC.P 04/25/06



726-24AC/10A 726-24AC/18A Power Supplies Specifications