

Full Data Module

7094A AES-IntelliPro™

Technical Specifications

DIMENSIONS

2.8 in H x 5.0 in W
(7.1 cm H x 12.7 cm W)

I/O CONNECTIONS

AES Subscriber with power
Easy programming using smartphone, tablet, or PC
Phone output from alarm panel
Trouble output (open collector)
For use with the 2.0 Burg unit 7007P-M and included with the 2.0 Burg 7007P-P-M
For 2.0 units only, not for use in Legacy units

POWER REQUIREMENTS

12 VDC nominal, primary and backup power provided by the AES RF Transceiver Unit

CURRENT

50mA normal

HOW TO ORDER

Models & Descriptions:

7094A - AES-IntelliPro 2.0 Burg accessory board (refer to 7094 for Legacy units)

7007P-M - 2.0 Burglary Subscriber with Upload/Download & Multiple Communication Technologies (MCT)

7007P-P-M - 2.0 Burglary Subscriber with Upload/Download, AES-IntelliPro, & MCT



Model 7094A AES-IntelliPro

The 7094A AES-IntelliPro is an add-on module for IntelliNet 2.0 Burglary Subscribers that enables transmission of full alarm zone data from an alarm panel to a central station over an established AES mesh radio network.

AES Subscribers with AES-IntelliPro can operate in applications with or without a phone line providing full emulation of the phone line for the alarm panel communicator. AES-IntelliPro supports most popular alarm communication protocols including Contact ID, Pulse.

Easy Installation

AES-IntelliPro easily installs in the 2.0 Burglary Subscriber housing and is powered from the transceiver module, requiring no additional power connections. 2.0 Burglary Subscribers can be ordered with AES-IntelliPro installed and is easy to program using smartphone, tablet, or PC.

Features

- Transmit full alarm data from any Contact ID or Pulse format alarm panel to AES receiver
- Support for remote account administration
- Primary or back-up communications
- Universal wireless alarm transmitter supports most manufacturers' panels
- Easy to install in IntelliNet 2.0 Burglary Subscriber
- Easily programmable using smartphone, tablet, or PC
- Option to monitor telephone lines
- Phone line cut notification via radio